

SLS1143

A delicately scaled, modular system of interconnected elements and suspended LED luminaires.

suspenders[®]

Custom Assembly Instructions

SONNEMAN[®]
A WAY OF LIGHT

Suspenders® Product Information and Warnings

Important

- **Always disconnect the power before installing or replacing Luminaires and before cleaning or other maintenance.**
- **Consult a qualified, licensed electrician to ensure correct branch circuit conductor.**
- Please read all included assembly instructions and warnings carefully before installation. Contact Customer Service if you have any questions or concerns. Before installation, please confirm that the fixture is compatible with your supply voltage and dimming system, if present.
- LEDs are highly sensitive electronic devices, and must be treated with care. Do not open any factory sealed compartments, and avoid touching the LEDs with your hands or any object.
- Although all our fixtures are equipped with protective devices, LED electronic systems are vulnerable to power surges and supply variations. Do not install LED fixtures on the same circuit as any motors, appliances, or HVAC systems.
- Do not remove or bypass any LED Driver or Transformer that is provided with the fixture, and do not replace or substitute with another power supply.
- Remote Transformer installation must be done by a licensed electrician and in accordance with local building and electrical codes. Remote installations should be in an accessible location, as close to the fixture as possible. The appropriate wire gauge must be used to limit the voltage drop to no more than 5%.
- Fixtures must be wired in parallel on independent leads; do not "daisy chain" multiple fixtures together or wire them in series.
- All factory-made splices and connections must remain intact. LED circuits are carefully designed and built, and improper connections may damage the fixture.
- Any mounting hardware is provided for your convenience and should be used with discretion. Always use the appropriate hardware for the mounting surface.
- To avoid excessive voltage drop, the longest electrical path from the Power Feed to the furthest Luminaire should not exceed 30 feet.
- Suspenders® transformers can be loaded up to 80% of their rated wattage.
- Suspenders® transformers feature short-circuit protection with automatic recovery, and will resume operation once the short-circuit condition is removed.
- Suspenders® transformers have 24VAC output, and are dimmable with Electronic Low Voltage dimmers ONLY.
- Suspenders® must be installed in dry locations ONLY.

Step 1 - Power Feed

Shallow Single Double Power Feed Installation (Fig. 1):

1. Shut off power to the **outlet box**.
2. **For remote transformer use:** The **Transformer** must be installed in an accessible location in accordance with local electrical codes. You must use the appropriate wire gauge from the transformer to the Power Feed to limit the voltage drop to less than 5%.
3. Make appropriate electrical connections using wire nuts:
 - a. Connect the **Transformer's** live wire (black) to the live outlet box wire.
 - b. Connect the Transformer's neutral wire (white) to the neutral outlet box wire.
 - c. Connect the ground outlet box wire (green or uncoated) to the mounting plate using the green screw.
 - d. Connect one of the black **Power Feed** wires to one of the transformer output wires. Connect the other black Power Feed wire to the second transformer output wire.
 - e. Carefully place connections in outlet box.
4. Attach the **mounting plate** to the outlet box using the two (2) **screws**.
5. Attach Power Feed to mounting plate. Secure using **set screws** and included **Allen key**.
6. To adjust orientation of bushings:
Loosen set screws using included Allen key and rotate Power Feed to the desired position.




Fig. 1

Note

- This fixture is dimmable with Electronic Low Voltage (i.e., Trailing-Edge/Reverse Phase) type dimmers **ONLY**.

June 13, 2019

Step 2 - Power Bars

Linear Power Bar Assembly:

1. The Linear Power Bar comes with a spacer clip pre-installed at the center of the Power Bar. (Fig. 2)
2. If desired, the spacer clip can be removed using a Phillips screwdriver. (Fig. 3)



Fig. 2




Fig. 3

Step 3 - Power Bar Connector

In-Line Power Bar Connector:

1. Align **In-Line Connector** with **Power Bar** (Fig. 4) and press down firmly on the top of the Power Bars, while pressing up on the bottom of the Connector until the Power Bars clicks into place (Fig. 5).




Fig. 4









Fig. 5

Step 4 - Truss Connections

Truss Hanger System:

1. Where applicable: Install the **Mounting Bracket** to the ceiling with **Anchor** (if applicable) and **Screw**, then screw the **Post** onto the Mounting Bracket (Fig. 6).
2. Insert Extension or End **Arm** into the remaining slot of the **Bracket** and secure it with the provided **Arm Flat Head Screw** (Fig. 7).
3. Where applicable: Insert the **Cable** into the **Post** and adjust to the desired length: to shorten, push the Cable up; to lengthen, push in the **Plunger** while pulling down on the Cable, release the Plunger to lock. Cut off the excess Cable where it exits the Post (Fig. 7).
4. Remove **Cover Flat Head Screw** and **Bracket Cover** and align **Power Bar** with the **Bracket** (Fig. 8).
5. Insert **Power Bar** onto the **Bracket** and reattach the **Bracket Cover** with **Flat Head Screw** (Fig. 9).
6. Repeat step 3 and 4 for each **Bracket**.



June 13, 2019

Tier Definitions




Fig. 22

Canopy Top View



Fig. 23

Step 5 - Ceiling Hangers

Cable Ceiling Hanger Assembly:

1. Install the mounting bracket to the ceiling with anchor and screw, then screw the post onto the mounting bracket. (Fig. 10)
2. Pass the Ceiling Hanger cable through the Power Bar, then through the center hole of the cover, making sure the counter-sunk holes on the cover are facing up. Attach the cover to the Ceiling Hanger using the two small Phillips screws. (Fig. 11)
3. Insert the cable into the post and adjust to the desired length: to shorten, push the cable up; to lengthen, push in the plunger while pulling down on the cable, release the plunger to lock. Cut off the excess cable where it exits the post. (Fig. 12)



Fig. 10




Fig. 11




Fig. 12

In-Line Cable Ceiling Hanger Assembly:

1. Install the mounting bracket to the ceiling with anchor and screw, then screw the post onto the mounting bracket. (Fig. 13)
2. Insert the cable into the post and adjust to the desired length: to shorten, push the cable up; to lengthen, push in the plunger while pulling down on the cable, release the plunger to lock. Cut off the excess cable where it exits the post. (Fig. 14)
3. Press down firmly on the top of the Power Bar, while pressing up on the bottom of the Hanger, until the Power Bar clicks into place (Fig. 15). Repeat for the second Power Bar.

Note

- The In-Line Cable Ceiling Hanger makes an electrical connection between the two Power Bars and cannot be used to isolate separate circuits.



Fig. 13




Fig. 14




Fig. 15

June 13, 2019

Step 6 - Ceiling Hanger Arrangement




Fig. 24

| Ceiling Hangers | |
|-----------------|--------------|
| ○ | = 1XB02SB06K |
| □ | = 1XB02IB06K |

Step 7 - Power Feed Hanger/Power Tap

In-Line Power Tap Hanger:

1. Install **Double Cord Power Feed Hanger** to **Lower Power Bar** and connect to the **Power Feed** by inserting the exposed wires into the **Power Feed Bushings**. Secure by tightening the **Set Screws** with the included **Allen Key** (Fig. 16).
2. Install the **Upper Power Bar** between the two cords of the **Double Cord Power Feed Hanger** using appropriate hangers.
3. Remove **Cord Caps** from **Tap Hanger** by sliding them up and off the sides of the **Tap Hanger** (Fig. 17).
4. Position **Tap Hanger** under **Upper Power Bar** at junction with **Double Cord Power Feed Hanger** (Fig. 18). Press down firmly on top of the Upper Power Bar, while pressing up on the bottom of Tap Hanger, until Tap Hanger clicks into place (Fig. 19).
5. Press each cord into the slot on each side of the **Tap Hanger** (Fig. 20).
6. To secure cord electrical connection, align **Cord Cap** over slot on each side of the **Tap Hanger**, and position the notches on bottom of the Cord Cap to face toward Tap Hanger (Fig. 21), then firmly slide down into position (Fig. 7). Repeat on opposite side.




Fig. 16




Fig. 17




Fig. 18




Fig. 19




Fig. 20





Fig. 21

June 13, 2019

STEP 8 - Luminaires

Power-Precise Blade Mount Hanger and Power-Precise Bar-Mounted Aimable Light Engine:


1. Align **Hanger** with **Power Bar** (Fig. 25) and press down firmly on the top of the Power Bar, while pressing up on the bottom of the Plug, until the Power Bar clicks into place (Fig. 26).
2. Align **Light Engine** with **Blade Mount Hanger** (Fig. 25), connect Light Engine to Blade Mount Hanger (Fig. 26).
3. Secure **Light Engine** to **Blade Mount Hanger** by screwing on **Retention Ring** (Fig. 27).



Power-Precise Direct Mount:

1. Align **Luminaire** with **Power Bar** (Fig. 28), press up firmly on the bottom of the Luminaire, while pressing down on the top of the Power Bar, until the Power Bar clicks into place (Fig. 29).

Note: Precise Direct Mount Luminaires can be assembled on top or on the bottom of the **Power Bar**.



STEP 9 - Trims

Connecting a Trim to a Cylinder Light Engine:

1. Insert the **Trim Ring** into the **Shade**. (Fig. 30)
2. Screw the **Trim Ring** into the **Cylinder Light Engine**. (Fig. 31)




Fig. 30




Fig. 31




Fig. 32

Power Precise Round Trims:

1. Align the **Lens**, **Shade**, and **Bezel** with each other (Fig. 33) then preassemble them together (Fig. 34).
2. Align the assembly from step 1 with the **Light Engine** (Fig. 35).
3. Screw the assembly from step 1 to the **Light Engine** (Fig. 35).




Fig. 33




Fig. 34




Fig. 35

June 13, 2019

Luminaire Locations

Locate the luminaires as shown in Fig 36. Follow instructions from steps 8 and 9.




Fig. 36

| Luminaires | |
|------------|----------------|
| ○ | = 1XDXXRH03K |
| □ | = 1XDXXCH04K-X |