

ASSEMBLY INSTRUCTIONS

ITEM DESCRIPTION:

ITEM NO.: GDDWI01 NAME: Chene Sconce

MATERIAL TYPE: Glass FINISH: Clear

SOCKET TYPE: E12 TYPE B SOCKET QTY: 01

BULB WATTAGE: 40W BULB / 10W SBCFL / 9 W SBLED

VOLTAGE: 125V ITEM NET WEIGHT: 2.6LBS



PARTS INCLUDED:

Mounting Plate	Qty:	1
Back Plate	Qty:	1
Glass Shade	Qty:	1
Metal Leafs	Qty:	3
Metal Shade Ring	Qty:	1

HARDWARE INCLUDED:

Mounting Screws	Qty:	02
Plastic Wire Connector	Qty:	02
Canopy Screw	Qty:	02
Screw Capes	Qty:	02

TOOLS NEEDED (Not Included):

1 Screwdriver

These instructions are provided for safety. It is very important that they are read carefully and completely before beginning installation

We strongly suggest that all hard-wired fixtures must be installed by a professional electrician.

For customer service questions call 1-800-338-2150



- Do not throw away packaging materials until assembly is complete.
- This wall sconce can be mounted vertically only.

TO ASSEMBLE:

1. Turn off the main electrical power supply from the main fuse box/circuit breaker.

2. Attach the mounting plate to the wall or junction box using the mounting screws (C).

3. Connect the ground wire from the wall to the ground wire of the fixture using wire caps (A).

4. Attach house wire to lamp wires as shown. Fasten the pairs together with a wire caps. **DO NOT REVERSE THE HOT AND NEUTRAL CONNECTIONS OR SAFETY WILL BE COMPROMISED.**

5. Attach the front face of the light to the back plate by inserting the canopy screws (B) through the pre-drilled holes in the front face and tightening both upper and lower screws using a screwdriver. Then, place the screw caps over the screws and secure them by turning clockwise.

6. Place a silicone washer on the bulb holder cover. Position the glass shade onto the holder, then add another silicone washer above the glass for safety. Attach the leaf rings one by one in the required position. Finally, secure the assembly by tightening the metal shade ring clockwise.

7. Insert **(1) TYPE 40W BULB / 10W SBCFL / 9 W SBLED** (not included) into the socket. **DO NOT EXCEED SPECIFIED WATTAGE**

8. Restore power to junction box and test fixture.

CARE INSTRUCTIONS:

Wipe with a soft, dry cloth. To protect finish, avoid the use of chemicals and

A R T E R I O R S