



FIXTURE INSTALLATION

1. Attach the MOUNTING PLATE (A) onto the junction box using the MOUNTING SCREWS (B). This fixture is designed to be mounted on standard junction box. The junction box must be securely mounted to the structure of the building.
2. Feed the wire through the STEM (T) and twist tightly onto the METAL SHADE (O) and FIXTURE ASSEMBLY (Q). Continue to Feed wires through STEM KIT (N) Keep adding additional stems until you desired hanging height is met.
3. Slide the CONNECTOR (M), CANOPY (L), WASHER (I) and HEX NUT (H) onto the STEM KIT (N), and secure them onto the top end of the STEM KIT (N).
4. Trim off the excess wire to a minimum 6" beyond the STEM and strip each wire $\frac{5}{8}$ ".
5. Attach the Ground wire (Green) to the ground inside the outlet box (Generally green or bar copper wire) or the GROUND SCREW (C) on the MOUNTING PLATE (A). NEVER CONNECT GROUND WIRE TO "HOT" WIRE! FAILURE TO FOLLOW THIS COULD RESULT IN SERIOUS INJURY OR DEATH!
6. Connect the white fixture lead to the neutral (Generally white) wire in the outlet box. Fasten the wires together with an approved fastener (WIRE NUT) (D). Starting 1" below the fastener, tightly wrap the connection with electrical tape so that the connections seals the end of the fastener. MAKE SURE THERE ARE NO EXPOSED WIRE OF STRANDS THAT COULD CAUSE A DANGEROUS SHORT CIRCUIT!
7. Connect the black fixture leads to the hot (Generally black) wire in the junction box. Fasten the joined wires same as previous step. NEVER REVERSE HOT AND NEUTRAL WIRES. FAILURE TO FOLLOW THIS COULD RESULT IN SERIOUS INJURY OR DEATH!
8. Lock the BRACKET (J) to the NIPPLE (E) using NUT (K). Push the wires back into the junction box. Lift up the CANOPY (L) up to the ceiling and secure on the 1/4 NIPPLE (E) with the COVER (F) and CAP NUT (G).
9. Screw the BULB (P) up into the SOCKET of the fixture. THIS FIXTURE IS RATED FOR MAX 15 WATT LED TYPE R20 LAMP. DO NOT EXCEED THE RECOMMENDED WATTAGE!
10. Lift the MARBLE (R) to the FIXTURE ASSEMBLY (Q) using the HEX NUT (H) and FINIAL (S).
11. Restore power to the outlet at the breaker or fuse box.

PART(S)	REPLACEMENT PART NAME	NUMBER
A,B,C,D,E,F	HARDWARE KIT	HDW-8336
G	CAP NUT	CPN-8336
H,I,J,K,L,M	CANOPY ASSEMBLY	CAS-8336
N	STEM KIT	STM-BSI300-SET
R	MARBLE	MBL-8336
S	FINIAL	FIN-8336
T	STEM	STM-8336