




IRIS SERIES PENDANT

DESIGNER
CAINE HEINTZMAN

INSTRUCTIONS



SCAN HERE



NORTH AMERICA



a-n-d.com

INSTALLATION NOTES

A low voltage Class 2 constant current LED driver is required to operate the luminaire. The LED driver varies, depending on input voltage and dimming requirements.

It is recommended that three people install the Iris Pendant; one to gently support the luminaire while the other makes the electrical and mechanical connections to the ceiling.

For questions regarding installation, please email info@n-d.com



CARE INSTRUCTIONS

Always wear clean gloves when handling the luminaire. Clean finished surfaces with a soft, lint-free cloth. Clean acrylic diffuser with a soft lint-free cloth and a diluted solution of dish soap in warm water.

For replacement parts contact A-N-D directly.



WARNING

The luminaire must be installed by a qualified electrician in a dry indoor location.

Failure to meet any or all of these criteria will not only damage the luminaire, but will void both the warranty and all of its certifications.

COMPONENTS



① BACKPLATE

② #8-32 SCREW (2)

③ LED DRIVER

④ TERMINAL (4)

⑤ BRACKET ASSEMBLY

⑥ BRACKET SCREW (2)

⑦ CANOPY

⑧ CANOPY SCREW

⑨ SLIDER

⑩ POWERED SUSPENSION WEBBING


⑪ NON POWERED SUSPENSION WEBBING (2)

⑫ SLIDER WASHER

⑬ SLIDER SCREW

⑭ LIGHT ASSEMBLY

⑮ BELT CLOSURE




* IRIS COMBO B/A
MODEL SHOWN

IRIS OPTIONS

IRIS COMBO A/A

13 lbs / 6 kg


∅ 15cm
6"



IRIS COMBO A/B

13 lbs / 6 kg


∅ 15cm
6"



IRIS COMBO B/A

13 lbs / 6 kg

∅ $\frac{15\text{cm}}{6''}$



30cm
11.8"

15cm
5.9"


90cm \approx 35.4"

IRIS COMBO B/B

13 lbs / 6 kg

∅ $\frac{15\text{cm}}{6''}$

300cm
118"



15cm
5.9"

15cm
5.9"

90cm \approx 35.4"

IRIS SLIDER POSITION

The Iris Pendant is characterized by its machined aluminum slider.


This component allows the customer to change the fixture's aesthetic by just sliding it on the suspension webbing.

Note that the slider position will affect the total drop height of Iris.



Moving the slider from the highest position to the lowest position, while suspended at 300cm / 118" will reduce the total drop height by about 20cm / 7.9".

Refer to this page when ready to trim the excess suspension webbing at Step 11.




REFER TO THIS PAGE WHEN AT STEP 11

SLIDER IN HIGHEST POSITION

SLIDER IN MIDDLE POSITION

SLIDER IN LOWEST POSITION



MINIMUM SLIDER'S DISTANCE FROM TOP LENS

LED DRIVER OPTIONS

The Iris Pendant LED driver varies depending on dimming requirements and input voltage.

Use the ordering code to determine the driver selected:

ie. IRI-90-P-A-B-BLK-27-010-277

DIMMING ----- INPUT VOLTAGE


PHASE CUT DIMMING (PC)

EUCHIPS PUP40T-ILMC-1200

INPUT: 120VAC

OUTPUT: 35VDC, 34W

L x W x H: 121 x 44 x 26.5




0-10 DIMMING (010)

EUCHIPS PUP40T-IWMC-1200

INPUT: 110-240VAC

OUTPUT: 35VDC, 34W

L x W x H: 121 x 44 x 26.5



PREPARATION


STEP 1

Mount the backplate to the ceiling.

Use the provided #8-32 screws.
Anchors, if needed, provided by installer.

Caution!

Ensure that the power is disconnected at the breaker.




STEP 2

Connect the primary circuit on the LED driver to input power. Connect ground.

Black/brown wire = **Line** (L)

White/blue wire = **Neutral** (N)

Green screw = **Ground** (G)




INSTALLATION


STEP 3

Iris comes pre-assembled with a 300cm / 118" drop height.

Leave the assembly in box up to suspending.



PRE-SET HEIGHT



300cm
118"

 **DO NOT CUT ANY WEBBING**


STEP 4

Identify the powered suspension webbing bracket plate and loosen it.

Use the provided hex key to loosen the two screws.

⚠ Attention!

Do not completely unscrew the bracket plate.



⚠ DO NOT CUT ANY WEBBING




INSTALLATION

STEP 5

Gently pull the powered suspension webbing from the bracket.

The length you will pull from the bracket will lift the fixture by the same amount.

i.e. pulling 100cm/39" up through the bracket will lift the fixture by 100/39"cm.




 **DO NOT CUT ANY WEBBING**

STEP 6

Re-tighten the bracket plate.

Use the provided hex key to secure the plate on the bracket.




INSTALLATION

STEP 7

Repeat steps 4, 5 and 6 for the other two bracket plates.

⚠ Attention!

Check that every suspension webbing is being pulled equally up through the bracket.




STEP 8

Carefully remove the light assembly from the box and put aside.

⚠ Caution!

Do not twist the suspension webbing.




⚠ DO NOT CUT ANY WEBBING

INSTALLATION

STEP 9

While supporting the luminaire's weight, install the bracket on the backplate with the provided bracket screws (M6X10).




STEP 10

Check the fixture levelness.

If required, micro adjustments can be made by repeating **STEPS 4 – 7**. It is possible to repeat these steps while the bracket is already installed on the backplate.

Caution!

While supporting the luminaire's weight, adjust one suspension webbing at a time.



DO NOT CUT ANY WEBBING


INSTALLATION

STEP 11

⚠ Attention!
Before trimming excess webbing and wires,
ensure height is correct.

Leave an extra 15cm / 6" of suspension webbing.

CUT EXCESS SUSPENSION
WEBBING AND WIRES




REFER TO PAGE 6: IRIS SLIDER OPTIONS

STEP 12

Connect the luminaire to secondary circuit on LED driver.

Red = **Positive** (V+)


Green = **Negative** (V-)



INSTALLATION

STEP 13

Using the provided canopy screw (M4x10), mount the canopy on the bracket.



STEP 14


While supporting the luminaire's weight, **Adjust the slider position as desired and fasten the position using the slider washer and screw.**

⚠ Caution!

Align the slider washer's notch with the powered suspension webbing.

⚠ Attention!

Moving the slider will affect the drop height of the light.



REFER TO PAGE 6: IRIS SLIDER OPTIONS



For support, please contact:

info@n-d.com

+1 604 563 6938

A-N-D

1951 Franklin St,
Vancouver, BC
Canada V5L 0C7

n-d.com