


ROMEO MOON S1

Designed by Philippe Starck, 1996


F6105000



ROMEO MOON S1

F6105000

EN




- 01. RF81836 – Ceiling rose assembly
- 02. RF6110800 – Kit with brass wire clamps and screws
- 03. RF29875 – Steel cable pack (3 cables) 3mt.
- 04. RF85863 – Lamp holder assembly
- 05. RF05974 – Anti-dust screen
- 06. RF6105200 – Moon S1 safety support ring assembly
- 07. RF03172 – Acid-etched diffuser
- 08. RF6110400 – Romeo Moon S1/T1 crown
- 09. RF02784 – Lamp holder support

ROMEO MOON S1 F6105000


EN

RF81836

CEILING ATTACHMENT ASSEMBLY



Romeo
Moon S1
p.03



Romeo
Moon S2
p.03

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

RF81836

CEILING ATTACHMENT ASSEMBLY




Fig.1

Disassemble the cable stopper (A), remove the safety split pins (B), unscrew the knurled nuts (C) and adjustment ring (D).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

RF81836

CEILING ATTACHMENT ASSEMBLY




Fig.2

Fix the wall attachment (E) utilizing appropriate expansion bolts.
REMARKS! Select and utilize screw plugs which are suitable for the surface where the assembly is to be installed.
 Assemble the adjustment balance ring by tightening the milled bolts and insert the safety cotter pins.

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON S1 F6105000


EN

RF6110800


KIT WITH BRASS WIRE CLAMPS AND SCREWS



Ray S1
p.06



Romeo
Moon S1
p.06



Romeo
Moon S2
p.06

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON S1 F6105000

EN

RF6110800

KIT WITH BRASS WIRE CLAMPS AND SCREWS




Fig.1

Insert the steel wires (L) through the relevant cable-clamps of the control ring,
as shown in the image.
Adjust them to the desired length and cut off any excess. Fix in place by
tightening the screws.

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.


©2021 Flos - All rights reserved - www.flos.com
Flos reserves the right to introduce any changes to its own models, without prior notice.

ROMEO MOON S1 F6105000


EN

RF29875

STEEL CABLE PACKED 3 PIECES MT.3




Ktribe S2
p.07



Ktribe S3
p.07



Romeo
Moon S1
p.08



Romeo
Moon S2
p.08

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON S1 F6105000

EN

RF29875

STEEL CABLE PACKED 3 PIECES MT.3




Fig.1

Let the suspension cables (F) go through the steel ring (G) thereafter into the supporting ring (H).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON S1 F6105000

EN

RF29875

STEEL CABLE PACKED 3 PIECES MT.3




Fig.2

Position the ends of the suspension cables into the holes (L) of the adjusting ring, paying attention to keep the cable stoppers outside the said ring.

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON S1 F6105000

EN

RF29875

STEEL CABLE PACKED 3 PIECES MT.3




Fig.3

Insert the diffuser (O) in the crown (P).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

©2021 Flos - All rights reserved - www.flos.com
Flos reserves the right to introduce any changes to its own models, without prior notice.

ROMEO MOON S1 F6105000

EN

RF29875

STEEL CABLE PACKED 3 PIECES MT.3




Fig.4

To adjust the length of the power cord (P), disconnect it from the terminal board and cut it to the desired length. Reconnect to the terminal board. Insert the dust shield (Q).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON S1 F6105000

EN

RF29875

STEEL CABLE PACKED 3 PIECES MT.3




Fig.5

To balance the crown (N), act on the knurled nuts (O).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON S1 F6105000

EN

RF29875

STEEL CABLE PACKED 3 PIECES MT.3




Fig.6

Attach the wires to the terminal board (R). Close the rosette (S) to the wall attachment (E) by fixing with nipple (A).


WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON S1 F6105000


EN

RF85863

LAMP HOLDER ASSEMBLY



Romeo
Moon S1
p.15



Romeo
Moon S2
p.15

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

RF85863

LAMP HOLDER ASSEMBLY




Fig.1

Remove the anti-dust screen (A) by bending the sides of the screen and removing it from the electrical cable.



Fig.2

Pull-out the damaged lamp holder assembly (B) from the appliance.
Unhook the three lamp supports (C) from the lamp holder assembly (B).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON S1 F6105000

EN

RF85863

LAMP HOLDER ASSEMBLY




Fig.3

Unfasten the plastic nut (D) and lower down the ceiling coupling (S) from the ceiling attachment (E).

Disconnect the electrical conductors from the terminal box (R).

Free the electrical wire by sliding it out from the ceiling coupling (S) and from the plastic nut (D).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON S1 F6105000

EN

RF85863

LAMP HOLDER ASSEMBLY




Fig.4

Assemble now the new spare-part:

Insert the electrical cable (P) through the plastic nut (D) and then through the ceiling coupling (S).

Adjust the length of the electrical cable (P).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

RF85863

LAMP HOLDER ASSEMBLY




Fig.5

Connect the electrical conductors to the terminal box (R). Assemble the ceiling coupling (S) to the ceiling attachment (E) by fastening the plastic nut (D).



Fig.6

Hook the three supports (C) to the lamp holder assembly (B). Collocate the electrical assembly (B) inside the internal glass diffuser (C), ensuring that the three lamp holder supports are hooked on the three openings (D) present on the glass diffuser (C).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON S1 F6105000

EN

RF85863

LAMP HOLDER ASSEMBLY




Fig.7

Insert the anti-dust screen (A) by bending the sides of the screen and inserting it through the electrical cable.


WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON S1 F6105000

EN

RF05974

ANTI-DUST SCREEN



WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON S1 F6105000

EN

RF05974

ANTI-DUST SCREEN




Fig.1

Insert the anti-dust screen (A) by bending the sides of the screen and inserting it through the electrical cable.

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON S1 F6105000

EN

RF6105200

SAFETY RING ASSEMBLY



WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

©2021 Flos - All rights reserved - www.flos.com
Flos reserves the right to introduce any changes to its own models, without prior notice.

ROMEO MOON S1 F6105000

EN

RF6105200

SAFETY RING ASSEMBLY



Fig.1



Fig.2



Fig.3




Fig.4

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

RF6105200

SAFETY RING ASSEMBLY




Fig.5



Fig.6



Fig.7



Fig.8

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON S1 F6105000

EN

RF6105200

SAFETY RING ASSEMBLY



Fig.9

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

©2021 Flos - All rights reserved - www.flos.com
Flos reserves the right to introduce any changes to its own models, without prior notice.

ROMEO MOON S1 F6105000

EN

RF03172

ACID-ETCHED DIFFUSER



WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON S1 F6105000

EN

RF03172

ACID-ETCHED DIFFUSER




Fig.1

Remove the anti-dust screen (A) by bending the sides of the screen and removing it from the electrical cable.

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON S1 F6105000

EN

RF03172

ACID-ETCHED DIFFUSER



Fig.2

Pull-out the electrical assembly (B) from the appliance.



Fig.3

Insert the new internal glass diffuser (C).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

RF03172

ACID-ETCHED DIFFUSER




Fig.4

Collocate the electrical assembly (B) inside the internal glass diffuser (C), ensuring that the three lamp holder supports are hooked on the three openings (D) present on the glass diffuser (C).




Fig.5

Insert the anti-dust screen (A) by bending the sides of the screen and inserting it through the electrical cable.


WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON S1 F6105000

EN

RF6110400

ROMEO MOON CROWN



Romeo
Moon S1
p.31



Romeo
Moon T1
p.05


WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON S1 F6105000

EN

RF02784

LAMP HOLDER SUPPORT



WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

©2021 Flos - All rights reserved - www.flos.com
Flos reserves the right to introduce any changes to its own models, without prior notice.

ROMEO MOON S1 F6105000

EN

RF02784

LAMP HOLDER SUPPORT




Fig.1

Remove the anti-dust screen (A) by bending the sides of the screen and removing it from the electrical cable.

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON S1 F6105000

EN

RF02784

LAMP HOLDER SUPPORT



Fig.2

Remove the lamp holder from its support and disconnect the electrical wires by pressing the push terminals with a paper clip (E) or something similar.



Fig.3

Collocate the electrical assembly (B) inside the internal glass diffuser (C), ensuring that the three lamp holder supports are hooked on the three openings (D) present on the glass diffuser (C).

Insert the anti-dust screen (A) by bending the sides of the screen and inserting it through the electrical cable.(Fig.1 page 33)

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.