


ROMEO MOON T1

Designed by Philippe Starck, 1998


F6107000



ROMEO MOON T1

F6107000

EN



- 01. RF03206 – T1 cover ring
- 02. RF6110400 – Romeo moon S1/T1 crown
- 03. RF03201 – Acid-etched diffuser
- 04. RF6100200 – Kit of screws & bolts for Romeo
- 05. RF05369 – S1/T1 bracket ring
- 06. RF04169 – E27 Lamp holder
- 07. RF32262 – Led dimmer 1004P LFP100-240V 4-150WHL 4-25W
- 08. RF02813 – T1 grey support bracket
- 10. RF6138100 – Kit of transparent pads for base

ROMEO MOON T1 F6107000

EN

RF03206

T1 COVER RING



WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

©2021 Flos - All rights reserved - www.flos.com
Flos reserves the right to introduce any changes to its own models, without prior notice.

ROMEO MOON T1 F6107000

EN

RF03206

T1 COVER RING




Fig.1

Place the glass shade (P) on the support ring (D).
Rest the covering ring (M) on the internal glass diffuser (L).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.


©2021 Flos - All rights reserved - www.flos.com
Flos reserves the right to introduce any changes to its own models, without prior notice.

ROMEO MOON T1 F6107000

EN

RF6110400

ROMEO MOON S1/T1 CROWN



Romeo
Moon S1
p.31



Romeo
Moon T1
p.05

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON T1 F6107000

EN

RF6110400

ROMEO MOON S1/T1 CROWN




Fig.1

Place the glass shade (P) on the support ring (D).
Rest the covering ring (M) on the internal glass diffuser (L).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

©2021 Flos - All rights reserved - www.flos.com
Flos reserves the right to introduce any changes to its own models, without prior notice.

ROMEO MOON T1 F6107000

EN

RF03201

ACID-ETCHED DIFFUSER



Romeo
Soft T1
p.09



Romeo
Moon T1
p.07

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON T1 F6107000

EN

RF03201

ACID-ETCHED DIFFUSER




Fig.1

Remove the lamp bulb (I) if still present on the lamp device.

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

©2021 Flos - All rights reserved - www.flos.com
Flos reserves the right to introduce any changes to its own models, without prior notice.

ROMEO MOON T1 F6107000

EN

RF03201

ACID-ETCHED DIFFUSER




Fig.2

Insert the diffuser (H).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON T1 F6107000

EN

RF03201

ACID-ETCHED DIFFUSER




Fig.3

Insert the lamp-bulb (I).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON T1 F6107000

EN

RF03201

ACID-ETCHED DIFFUSER




Fig.4

Place the glass shade (P) on the support ring (D).
Rest the covering ring (M) on the internal glass diffuser (L).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

©2021 Flos - All rights reserved - www.flos.com
Flos reserves the right to introduce any changes to its own models, without prior notice.

ROMEO MOON T1 F6107000

EN

RF6100200

KIT OF SCREWS/BOLTS FOR ROMEO



Romeo
Moon F
p.12



Romeo
Moon T1
p.12



Romeo
Soft F
p.12



Romeo
Soft T1
p.14

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON T1 F6107000

EN

RF6100200

KIT OF SCREWS/BOLTS FOR ROMEO




Fig.1

Rest the support ring (D) on the support brackets (E) and lock it by fastening it with the screws (F).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON T1 F6107000

EN

RF6100200

KIT OF SCREWS/BOLTS FOR ROMEO




Fig.2

Insert the lamp-bulb (I).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

©2021 Flos - All rights reserved - www.flos.com
Flos reserves the right to introduce any changes to its own models, without prior notice.

ROMEO MOON T1 F6107000

EN

RF6100200

KIT OF SCREWS/BOLTS FOR ROMEO




Fig.3

Place the glass shade (P) on the support ring (D).
Rest the covering ring (M) on the internal glass diffuser (L).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

©2021 Flos - All rights reserved - www.flos.com
Flos reserves the right to introduce any changes to its own models, without prior notice.

ROMEO MOON T1 F6107000

EN

RF05369

SUPPORT RING



Romeo
Moon T1
p.16



Romeo
Soft T1
p.17

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON T1 F6107000

EN

RF05369

SUPPORT RING




Fig.1

Rest the support ring (D) on the support brackets (E) and lock it by fastening it with the screw/pivots (F).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON T1 F6107000

EN

RF05369

SUPPORT RING




Fig.2

Insert the diffuser (H).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

©2021 Flos - All rights reserved - www.flos.com
Flos reserves the right to introduce any changes to its own models, without prior notice.

ROMEO MOON T1 F6107000

EN

RF05369

SUPPORT RING




Fig.3

Insert the lamp-bulb (I).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

©2021 Flos - All rights reserved - www.flos.com
Flos reserves the right to introduce any changes to its own models, without prior notice.

ROMEO MOON T1 F6107000

EN

RF05369

SUPPORT RING




Fig.4

Place the glass shade (P) on the support ring (D).
Rest the covering ring (M) on the internal glass diffuser (L).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON T1 F6107000

EN

RF04169

E27 LAMP HOLDER



Romeo
Moon F
p.21



Romeo
Moon T1
p.21



Romeo
Soft F
p.17



Romeo
Soft T1
p.22

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

RF04169

E27 LAMP HOLDER




Fig.1




Fig.2

Remove the cover ring (O).
Remove the fabric lamp shade (N) by
unfastening the small bolts (Q).
Unhook the fabric shade from the support ring
(D).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

RF04169

E27 LAMP HOLDER




Fig.3

Remove the lamp-bulb (I) if still present on the lamp device.




Fig.4

Remove the diffuser (H).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

RF04169

E27 LAMP HOLDER




Fig.5

Remove the support ring (D) from the support brackets (E) by unfastening the screw/pivot.




Fig.6

Unfasten the three locking screws (A) of the lamp counterweight (B) present underneath the lamp base.
Remove the counterweight (B) and unfasten the two clamps screws.

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON T1 F6107000

EN

RF04169

E27 LAMP HOLDER



Fig.7

Unfasten the two screws (N) and lift up the lamp holder assembly (O) with his bracket.




Fig.8

Push down the brass hook (A).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON T1 F6107000

EN

RF04169

E27 LAMP HOLDER




Fig.9

Unfasten the sleeve (C) of the lamp holder.




Fig.10

Disconnect the electrical conductors (D) from the terminals of the lamp holder contacts.

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

©2021 Flos - All rights reserved - www.flos.com
Flos reserves the right to introduce any changes to its own models, without prior notice.

RF04169

E27 LAMP HOLDER




Fig.11

Unfasten the screw of the cable clamp (E) and slide it off from the electrical cable.



Fig.12

Slide off the isolator (F) from the electrical cable.

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

RF04169

E27 LAMP HOLDER




Fig.13

Unfasten the internal screw (G) of the lamp holder support (H).




Fig.14

Remove the lamp holder support (H) from the bracket (I) by unfastening the nut (J) with a pair of adjustable pliers (K).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

©2021 Flos - All rights reserved - www.flos.com
Flos reserves the right to introduce any changes to its own models, without prior notice.

RF04169

E27 LAMP HOLDER



Fig.15

Assemble now the new spar-part:

Fasten the new lamp holder support (H) on the threaded pin (L).

Fasten it well by fastening the nut (J) with the adjustable plier (K).

Fasten the internal screw (G) present inside the lamp holder support (H). Slide through the electrical cable the isolator (F) and position it inside the lamp holder support (H).(Fig.12-13 page 27-28)

Insert the cable clamp (E) and fasten the locking screw.

Connect the electrical wires (D) to the terminals of the lamp holder contacts respecting the polarities (L = Brown – N = Blue).(Fig.11-10 page 26-27)

Fasten the sleeve (C) on the lamp holder support and push the brass hook (A) back in a way that it hooks on to the sleeve (C). (Fig.8-9 page 25-26)

Assemble the lamp holder (O) with bracket, by fastening the two locking screws (N).(Fig.7 page 25)




Fig.16

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

RF04169

E27 LAMP HOLDER



Fig.17

Fasten the internal screw (G) present inside the lamp holder support (H). Slide through the electrical cable isolator (F) and position it inside the lamp holder support (H).

Insert the cable clamp (E) and fasten the locking screw. (Fig.10-11 page 26-27)
Connect the electrical wires (D) to the terminals of the lamp holder contacts respecting the polarities (L=Brown – N=Blue).

Fasten the sleeve on the lamp holder support and push the brass hook (A) back in a way that it hooks on to the sleeve (C). (Fig.8 page 25)

Assemble the lamp holder (O) with bracket, by fastening the two locking screws (N). (Fig.7 page 25)

Fasten the two screws (C) of the cable clamp and then assemble the lamp counterweight (B) by fastening the three locking screws (A). (Fig.6 page 24)

Rest the support ring (D) on the support brackets (E) and lock it by fastening it with the screw/pivot. (Fig.5 page 24)

Insert the diffuser (H) and the lamp-bulb (I). (Fig.3-4 page 23)






Fig.18

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

RF04169

E27 LAMP HOLDER



Position the fabric lamp shade (N) on the support ring (D) ensuring to insert the hook threaded screws (R) into the apposite holes present in the support ring (D), fasten the small bolts (Q).

Collocate the silicone seats in there apposite holes underneath the cover ring (O).

Rest the covering ring (O) on the pins (G).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON T1 F6107000

EN

RF32262

LED DIMMER 1004P LFP100-240V 4-150WHL 4-25W



Bedside
Gun
p.12



Chiara T
p.03



Glo-ball
Basic 0
p.11



Glo-ball
Basic 1
p.14



Glo-ball
Basic 2
p.05



Glo-ball
T1
p.11



Ic T1
High
p.08



Ic T1
Low
p.08



Ic T2
p.08



Ktribe T1
p.05



Ktribe T2
p.05



Ray T
p.17



Romeo
Moon
T1
p.32



Romeo
Soft T1
p.32



Spun
Light
T1
p.12



Spun
Light
T2
p.12




Table
Gun
p.12

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON T1 F6107000

EN

RF32262

LED DIMMER 1004P LFP100-240V 4-150WHL 4-25W



Fig.1




Fig.2

Open the dimmer box of the damaged dimmer.
For the opening, it is necessary to remove the n°2 screws using a star screw driver.

Lift-up the dimmer casing from the dimmer base;

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON T1 F6107000

EN

RF32262

LED DIMMER 1004P LFP100-240V 4-150WHL 4-25W




Fig.3




Fig.3.1

Remove the cable clamps by unfastening the 4 screws (A) and disconnect the wires from the terminal blocks through a tiny flat headed screw driver;



Fig.4

Replace the dimmer and connect the wires. When connecting the wires it is necessary to respect the polarities (L = Brown and N = Blue) to the terminal box. Lock the electrical cables by fastening the screws (A) of the cable clamps and make sure to block the isolation of the electrical cable.

Close the dimmer box. It is necessary to place the casing on top and press down until it locks in. it is necessary to insert the n°2 screws using a star screw driver.

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON T1 F6107000

EN

RF02813

T1 GREY SUPPORT BRACKET



Romeo
Moon T1
p.35



Romeo
Soft T1
p.35

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON T1 F6107000

EN

RF02813

T1 GREY SUPPORT BRACKET




Fig.1




Fig.2

Remove the cover ring (O).
Remove the fabric lamp shade (N) by
unfastening the small bolts (Q).
Unhook the fabric shade from the support ring
(D).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

©2021 Flos - All rights reserved - www.flos.com
Flos reserves the right to introduce any changes to its own models, without prior notice.

ROMEO MOON T1 F6107000

EN

RF02813

T1 GREY SUPPORT BRACKET




Fig.3

Remove the lamp-bulb (I) if still present on the lamp device.




Fig.4

Remove the diffuser (H).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

RF02813

T1 GREY SUPPORT BRACKET




Fig.5

Remove the support ring (D) from the support brackets (E) by unfastening the screw (F).




Fig.6

Unfasten the locking screw of the lamp counterweight present underneath the lamp base.
Remove the counterweight (B) and unfasten the two clamp screw.

ROMEO MOON T1 F6107000

EN

RF02813

T1 GREY SUPPORT BRACKET



Fig.7

Unfasten the two screws (N) and lift up the lamp holder assembly (O) with his bracket.




Fig.8

Unfasten the two locking screws (P) and remove the damaged support bracket (E).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

©2021 Flos - All rights reserved - www.flos.com
Flos reserves the right to introduce any changes to its own models, without prior notice.

ROMEO MOON T1 F6107000

EN

RF02813

T1 GREY SUPPORT BRACKET



Fig.9




Fig.10

Assemble now the new spare-part:

Collocate the new support bracket (E), ensuring that the holes (Q) present on the bracket correspond with the holes (R) present on the lamp cup (O).

Assemble the support bracket (E) by fastening the two screws (P).

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off. For the installation of the spare-part, it is necessary to consult a qualified electrician.

RF02813

T1 GREY SUPPORT BRACKET



Fig.11

Assemble the lamp holder (O) with bracket, by fastening the two locking screws (N).



Fig.12

Fasten the two screws (C) of the cable clamp and then assemble the lamp counterweight by fastening the three locking screws. (Fig 6 page 38)

Rest the support ring (D) on the support brackets (S) and lock it by fastening it with the screws (F).

Insert the diffuser (H). (Fig. 4-5 page 37-38)

Insert the lamp-bulb. (Fig. 3 page 37)

Place the glass shade (P) on the support ring (D).

Rest the covering ring (M) on the internal glass diffuser (L). (Fig. 1 page 36)

ROMEO MOON T1 F6107000

EN

RF6138100

KIT OF TRANSPARENT PADS FOR LAMP BASE



Romeo
Moon T1
p.42



Romeo
Soft T1
p.42



Tatou T1
p.18

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

ROMEO MOON T1 F6107000

EN

RF6138100

KIT OF TRANSPARENT PADS FOR LAMP BASE



Fig.1

Stick-on the feet (A) to the base.

WARNING! When installing and whenever acting on the appliance, ensure that the power supply has been switched off.
For the installation of the spare-part, it is necessary to consult a qualified electrician.

©2021 Flos - All rights reserved - www.flos.com
Flos reserves the right to introduce any changes to its own models, without prior notice.