

ASSEMBLY INSTRUCTIONS

MON-001

Before you begin

1. Turn electricity off at main circuit breaker, remove the fixture body and associated components from the box, make sure that no parts are missing before assembling.
2. Gather all tools (if need) prior to assembly.

Important Safety Information:


THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. INSTALLATION BY A LICENSED ELECTRICIAN IS STRONGLY RECOMMENDED.



WARNING

To reduce the risk of fire, electrical shock, or injury:

- ENSURE ELECTRICAL BREAKER HAS BEEN SHUT OFF PRIOR TO INSTALLATION.
- Intended for use only indoors in a dry location.
- Read the instructions below carefully prior to installation and ensure that they are followed.
- Do not install on a radiant-heating type ceiling.



NOTE : The drawing of the lamp body is for reference only.

Made in China

CARE AND MAINTENANCE

- For indoor use only.
- Do not clean fixture with chemicals, solvents, harsh cleaners, or polish as they may damage the finish.
- Dust and clean using a soft dry or damp cloth.

How to Install HARE WIRE PENDANT LAMP:

A- Turn off circuit breakers and wall switch to the fixture supply line lead

Failure to disconnect power supply prior to installation may result in serious injury

B- Remove existing fixture and disconnect all electrical wiring.

C- Secure mounting plate (3) to outlet box with the mounting screws (4).

D- Connect fixture wires by using wire connectors (1): white wire to white (neutral) wire, black wire to black (live) wire and bare copper ground wire to ground screw terminal (2).

E- Secure canopy (5) to mounting plate (3) with the support screws and round nuts (6).

F- Install the shade (7) onto the socket and hold in place with the socket ring (8).

G- Insert bulb (9). Bulb not included. Surya recommends LED bulbs.



CAUTION: TO REDUCE RISK OF FIRE, USE **MAX 100-WATT TYPE A** LAMP OR USE MAXIMUM 13WATT SELF-BALLASTED LAMP OR LAMP ADAPTER. 120V 60Hz AC ONLY MADE IN CHINA E530608

ATTENTION: AFIN DE RÉDUIRE LE RISQUE D'INCENDIE, UTILISER UNE **MAX AMPOULE TYPE A** DE 100 WATTS OU UTILISER UNE **MAXIMUM 13 WATTS** AUTOBALLASTÉE LAMPE OU LAMPE ADAPTEUR. 120V 60Hz C.A. SEULEMENT FABRIQUÉ EN CHINE E530608