


ASSEMBLY INSTRUCTIONS



Fay 32" Chandelier

Item # IKF5110

NOTICE:

This light fixture should be installed in accordance with all applicable, local installation codes, and by a person familiar with the construction and operation of it, as well as the hazards involved. Inspect item and contents carefully. If any damage or defect is found, do not install. Retain all packaging material until installation is complete and approved.

TOOLS REQUIRED (NOT INCLUDED):

Phillips Screwdriver

Slotted Screwdriver

Chain Pliers

Slip Joint Pliers


Measuring Tape

Wire Cutters

Wire Strippers

1. Carefully remove all parts from the box. Place on a clean, soft surface.
2. Remove mounting plate (**B**) from canopy (**D**) by removing collar ring (**E**).
3. Install mounting plate (**B**) to junction box and secure with mounting screws (**C**).
4. Install driver (**N**) and canopy (**D**) to collar loop (**M**) and secure with collar ring (**F**).
5. Determine desired overall length, and amount of chain (**F**) needed. Shorten chain using chain pliers. (Keep extra chain)
6. Attach chain (**F**) to collar loop (**M**) and fixture loop (**G**) using quick links (**L**). Secure quick links (**L**).
7. Thread fixture wire and ground wire through chain (**F**).
NOTE: When you reach the collar loop (**M**), ensure there is no tension on the wires. Cut excess wires, being sure to leave enough to reach the junction box.
8. Separate two sides of molded wire, and strip insulation on each 5/8".
9. Loosen collar ring (**E**) and let canopy (**D**) and driver (**N**) slip down chain (**F**) carefully.
10. Twist all fixture wires together. Slip through center hole of collar loop (**M**).
NOTE: Untwist wires and separate to prepare for connection.

ASSEMBLY INSTRUCTIONS



Fay 32" Chandelier

Item # IKF5110

NOTICE:

This light fixture should be installed in accordance with all applicable, local installation codes, and by a person familiar with the construction and operation of it, as well as the hazards involved. Inspect item and contents carefully. If any damage or defect is found, do not install. Retain all packaging material until installation is complete and approved.

11. Wrap supply ground wire (usually green or bare copper) around the green grounding screw (see diagram 1). Tighten.
NOTE: It is imperative that the fixture is grounded.
12. Connect driver **(N)** input neutral wire (white) to the supply neutral wire (usually white) using wire nut **(A)**.
13. Connect driver **(N)** input hot wire (black) to the supply hot wire (usually black) using wire nut **(A)**.
CAUTION: Do not reverse the hot and neutral connections.
14. Connect fixture neutral wire (black) to driver **(N)** output wire (black) using wire nut **(A)**.
15. Connect fixture hot wire (red) to driver **(N)** output wire (red) using wire nut **(A)**.
CAUTION: Do not reverse the hot and neutral connections.
16. Make sure all wire connections are tight, then carefully tuck into the junction box.
17. Install driver **(N)** and canopy **(D)** to collar loop **(M)** and secure with collar ring **(E)**.
18. Install LED light source **(L)** to sockets **(H)**.
NOTE: All LED must be installed before testing or restoring power.
19. Place shades **(J)** onto LED light source **(L)**.

Care Instructions: Clean only with a soft dry cloth or feather duster. Do not use abrasive or chemical agents.