

# Assembly Instruction Sheet #S-1375P43 For Style 1375P43

Tools Required: Phillips screwdriver, Phillips screwdriver, pliers, wire cutters, wire strippers, electrical tape, safety glasses.  
Light Source(s): 120V LED 27W DIMMABLE (2000K)  
Precautions: Identify and inspect all parts before beginning installation. Check package content list and diagrams below to be sure all parts are present. If any parts are missing or damaged, do not attempt to assemble, install, or operate the fixture. Contact customer service for replacement parts.

**⚠ Warnings and Cautions**  
Turn off electricity at circuit breaker or main fuse box before installation. Consult a licensed electrician if in doubt.  
These instructions are provided for your safety. It is very important you read them completely before installing the fixture.  
We strongly recommend that a licensed, professional electrician perform the installation.  
Disconnect fixture from power source before replacing bulbs. Make sure bulbs are given sufficient time to cool before removal.

## Package Contents

- [A] Fixture Body** x1
- [B] Ceiling Canopy** x1
- [C] Middle Rod** x1
- B1 4" 2pcs  
B2 6" 1pcs  
B3 12" 3pcs

Hardware Contents	
PART	DESCRIPTION QUANTITY
BB	Wire nut 2pcs
CC	Screw 2pcs



## STEP 1 - Release Crossbar from Ceiling Canopy.



Figure 1

## STEP 2 - Install Ceiling Canopy to Ceiling




Figure 2

## STEP 3 - Wire Connections .




Figure 3

**STEP 4 - Attach Crossbar to Outlet Box.**  
A. Pass the supply wires through the Crossbar (BB). Attach the Crossbar (BB) to the Outlet Box (CC) with the head of the Green Ground Screw facing you. Secure it with Outlet Box Screws (not included). Tighten until snug.




Figure 4

## STEP 5 - Wire Connections

A. Use standard wire connectors (not included) to make all wire connections. Twist connectors until wires are tightly joined together. Wrap each connection with approved electrical tape and carefully stuff all the connected wires into the Outlet Box.




Figure 5

## STEP 6 - Install tube.




Figure 6