

PRODUCT FEATURES

- From the brand formerly known as Tech Lighting
- Simple yet stylish design
- Thin metal back plate for sleek minimalist look
- Provides up and down illumination
- ADA Compliant
- The LED Driver is housed within the junction box. (L. 3.03" | W. 1.22" | H. .83")



LAMPING

Includes 12 watt, 255 delivered lumen, 3000K LED module. Dimmable with low-voltage electronic dimmer. May be mounted vertically or horizontallyADA compliant.

Walnut /  
Satin Nickel



Walnut /  
Satin Nickel

ORDERING INFORMATION

700WSCAFE	FINISH	LAMP
	WS WALNUT/SATIN NICKEL	-LED930A LED 90 CRI 3000K 120V -LED930A-277 LED 90 CRI 3000K 277V


700WSCAFE

JOB NAME

NOTES

## SPECIFICATIONS

PRIMARY MATERIAL	Metal
SHADE MATERIAL	Acrylic
NET WEIGHT	2 lbs
HEIGHT	5in
WIDTH	3.6in
LENGTH	4.2in
MIN. EXTENSION FROM WALL	3.6in
UP LIGHT / DOWN LIGHT / BOTH?	
WET LISTED	
DAMP LISTED	
DRY LISTED	
UP / DOWN	
HORIZONTAL / VERTICAL	
WALL / CEILING MOUNT	
GENERAL LISTING	ETL Listed
ADA COMPLIANT	
INCLUDES	



## LAMPING SPECIFICATIONS

	LED LAMP	INTEGRATED LED	NON LED	NO LAMP
DELIVERED LUMENS		255		
WATTS		12		
MAX WATTAGE PER BULB		12W		
		120V ELV, TRIAC 277V 0-10V		
CCT		3000K		
CRI		90 CRI		
LED LIFETIME				
L70		>50000		
AVERAGE BULB HOURS				
FIELD SERVICEABLE LED				
LAMP BASE		Integrated LED		
LAMP SHAPE		Integrated LED		
LAMP INCLUDED?		True		
WARRANTY**		5 Years		

\* Dimming information available at [www.techlighting.com/Downloads#dimming](http://www.techlighting.com/Downloads#dimming)

\*\* Visit [techlighting.com](http://techlighting.com) for specific warranty limitations and details.

## T20 / T24 / JA8 INFORMATION

	Integrated LED	Replacement LED Lamp	No Lamp *
This product can be used to comply with California Building Energy Efficiency Standards 2016 Title 24 Part 6 / JA8.	Yes		
This product can be used to comply with California Appliance Efficiency Standards 2016 Title 20 and may be shipped to and sold in California.	N/A		

\* If a light fixture or component does not include a lamp or light source, it is the responsibility of the customer to select a lamp that meets the T24 and T20 requirements.

