

## PRODUCT FEATURES



- Hand-blown glass manufactured in Italy
- This item is made of natural brass. It is a living finish that will patina and warm with age which adds richness. If it gets an uneven patina or spots, a brass cleaner can restore the finish
- Remote and surface mount driver options available. An optional mud-in canopy kit can be ordered separately in conjunction with the 'Remote' driver option for the most minimal ceiling appearance.
- Contact factory for custom configurations
- Modern finishes available

## LAMPING

## ORDERING INFORMATION

COLOR TEMP	FINISH	LAMP
<b>27</b> 2700K	<b>BZ</b> BRONZE	<b>R</b> REMOTE
<b>30</b> 3000K	<b>HAB</b> HAND-RUBBED ANTIQUE BRASS	<b>R-277</b> REMOTE 277V
	<b>PN</b> POLISHED NICKEL	<b>S</b> SURFACE

JOB NAME \_\_\_\_\_

NOTES \_\_\_\_\_  
 \_\_\_\_\_  
 \_\_\_\_\_



## SPECIFICATIONS

PRIMARY MATERIAL	Brass
SHADE MATERIAL	Glass
NET WEIGHT	98 lbs
HEIGHT	511in
WIDTH	2.8in
LENGTH	2.8in
WET LISTED	
DAMP LISTED	
DRY LISTED	
GENERAL LISTING	ETL Listed
INCLUDES	

## LAMPING SPECIFICATIONS

LED LAMP	INTEGRATED LED	NON LED	NO LAMP
DELIVERED LUMENS	8076		
WATTS	224		
MAX WATTAGE PER BULB	224W		
INPUT VOLTAGE/ DIMMING TYPE	120V ELV, TRIAC 277V 0-10V 120V-277V ELV, TRIAC		
CCT	2700K 3000K		
CRI	90 CRI		
LED LIFETIME			
L70	>50,000		
AVERAGE BULB HOURS			
FIELD SERVICEABLE LED			
LAMP BASE	Dedicated LED		
LAMP SHAPE	Dedicated LED		
LAMP INCLUDED?	True		
WARRANTY**	5 Years		

\* Dimming information available at [www.techlighting.com/Downloads#dimming](http://www.techlighting.com/Downloads#dimming)

\*\* Visit [techlighting.com](http://techlighting.com) for specific warranty limitations and details.

## T20 / T24 / JA8 INFORMATION

	Integrated LED	Replacement LED Lamp	No Lamp *
This product can be used to comply with California Building Energy Efficiency Standards 2016 <b>Title 24</b> Part 6 / JA8.	No		
This product can be used to comply with California Appliance Efficiency Standards 2016 <b>Title 20</b> and may be shipped to and sold in California.			

\* If a light fixture or component does not include a lamp or light source, it is the responsibility of the customer to select a lamp that meets the T24 and T20 requirements.

