## INSTALLATION INSTRUCTION

# 2.5" Low Voltage - Metal Trim

HR-836



#### **SAFETY INSTRUCTION**

IMPORTANT: NEVER attempt any work without shutting off the electricity.

- Read all instructions before installing.
- This product must be installed in accordance with the applicable installation code by a person familiar with the construction and operation of the product and the hazards involved.
- System is intended for installation in accordance with National Electric Code, and local regulations.
- Consult with local inspector to assure compliance.
- To reduce the risk of fire, electrical shock and injuries to persons, turn off power at main switch before installing or modifying the system.
- · Warning: (Risk of fire) do not install insulation within 3 inches of fixture sides, or junction box, or in a manner to entrap heat.
- Retain instructions for future maintenance reference.

#### **OVERVIEW**

Trims fit housings from the HR-800 series. Housing type and trim selection will determine maximum wattage; consult catalog or spec sheet for compatibility

### **INSTALLING LAMP AND TRIM:**

- 1. From the front of trim, insert the MR16 lamp followed by the clear glass lens, and secure with the lens retaining ring.
- 2. Push socket on to lamp pins.
- 3. Pressing the springs into the hole, until the trim ring is flush against the ceiling.

